

Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	3,408	4,178	5,172	5,673
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	100	95	89	86
T2R	Lumens	3,648	4,473	5,536	6,074
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	107	102	95	92
T3	Lumens	3,482	4,270	5,285	5,797
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	102	97	91	88
T3R	Lumens	3,540	4,342	5,374	5,896
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	104	99	93	89
T4FT	Lumens	3,508	4,302	5,324	5,840
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	98	92	88
T4W	Lumens	3,440	4,218	5,222	5,727
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	101	96	90	87
SL2	Lumens	3,413	4,185	5,179	5,681
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	100	95	89	86
SL3	Lumens	3,476	4,264	5,277	5,788
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	102	97	91	88
SL4	Lumens	3,321	4,073	5,040	5,528
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
5NQ	Lumens	3,579	4,387	5,431	5,958
	BUG Rating	B2-U0-G0	B2-U0-G0	B2-U0-G1	B2-U0-G1
	Lumens per Watt	105	100	94	90
5MQ	Lumens	3,707	4,545	5,627	6,172
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	109	103	97	94
5WQ	Lumens	3,621	4,442	5,496	6,029
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	106	101	95	91
SLL/ SLR	Lumens	3,074	3,770	4,667	5,120
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	90	86	80	78
RW	Lumens	3,557	4,363	5,399	5,924
	BUG Rating	B2-U0-G1	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	105	99	93	90
AFL	Lumens	3,567	4,373	5,412	5,938
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	105	99	93	90

Nominal Power Lumens (2700K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	3,876	4,754	5,882	6,452
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	114	108	101	98
T2R	Lumens	4,150	5,088	6,298	6,910
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	122	116	109	105
T3	Lumens	3,961	4,858	6,012	6,595
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	117	110	104	100
T3R	Lumens	4,027	4,939	6,114	6,706
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	118	112	105	102
T4FT	Lumens	3,991	4,895	6,057	6,643
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	117	111	104	101
T4W	Lumens	3,914	4,799	5,941	6,515
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	115	109	102	99
SL2	Lumens	3,882	4,762	5,892	6,462
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	114	108	102	98
SL3	Lumens	3,955	4,851	6,003	6,584
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	116	110	104	100
SL4	Lumens	3,779	4,632	5,734	6,290
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	111	105	99	95
5NQ	Lumens	4,072	4,991	6,179	6,777
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B2-U0-G1
	Lumens per Watt	120	113	107	103
5MQ	Lumens	4,218	5,172	6,401	7,022
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	124	118	110	106
5WQ	Lumens	4,120	5,052	6,253	6,859
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	121	115	108	104
SLL/ SLR	Lumens	3,497	4,289	5,309	5,824
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	97	92	88
RW	Lumens	4,047	4,963	6,142	6,739
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	119	113	106	102
AFL	Lumens	4,057	4,974	6,158	6,754
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	119	113	106	102

Nominal Power Lumens (3000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	4,222	5,176	6,406	7,027
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	124	118	110	106
T2R	Lumens	4,519	5,541	6,858	7,525
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	133	126	118	114
T3	Lumens	4,313	5,290	6,547	7,182
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	127	120	113	109
T3R	Lumens	4,386	5,378	6,657	7,303
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	129	122	115	111
T4FT	Lumens	4,346	5,330	6,596	7,235
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	128	121	114	110
T4W	Lumens	4,262	5,226	6,469	7,095
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	125	119	112	107
SL2	Lumens	4,227	5,185	6,416	7,038
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	124	118	111	107
SL3	Lumens	4,307	5,282	6,537	7,170
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	127	120	113	109
SL4	Lumens	4,115	5,045	6,245	6,849
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	121	115	108	104
5NQ	Lumens	4,434	5,436	6,728	7,380
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	130	124	116	112
5MQ	Lumens	4,593	5,632	6,971	7,646
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	135	128	120	116
5WQ	Lumens	4,487	5,502	6,810	7,470
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	132	125	117	113
SLL/ SLR	Lumens	3,808	4,671	5,781	6,342
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	112	106	100	96
RW	Lumens	4,407	5,404	6,689	7,339
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	130	123	115	111
AFL	Lumens	4,418	5,417	6,705	7,356
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	130	123	116	111

Nominal Power Lumens (5000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	4,635	5,683	7,034	7,717
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	136	129	121	117
T2R	Lumens	4,962	6,084	7,531	8,262
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	146	138	130	125
T3	Lumens	4,736	5,808	7,189	7,886
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
T3R	Lumens	4,816	5,907	7,310	8,020
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	142	134	126	122
T4FT	Lumens	4,772	5,852	7,242	7,945
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	140	133	125	120
T4W	Lumens	4,679	5,738	7,103	7,791
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G2
	Lumens per Watt	138	130	122	118
SL2	Lumens	4,643	5,693	7,045	7,728
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G3
	Lumens per Watt	137	129	121	117
SL3	Lumens	4,729	5,800	7,178	7,873
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
SL4	Lumens	4,518	5,540	6,856	7,520
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	133	126	118	114
5NQ	Lumens	4,868	5,969	7,387	8,104
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	143	136	127	123
5MQ	Lumens	5,043	6,184	7,654	8,396
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	148	141	132	127
5WQ	Lumens	4,926	6,041	7,476	8,201
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	145	137	129	124
SLL/ SLR	Lumens	4,181	5,129	6,348	6,964
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	123	117	109	106
RW	Lumens	4,839	5,934	7,345	8,058
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	142	135	127	122
AFL	Lumens	4,852	5,948	7,362	8,077
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	143	135	127	122

Nominal Power Lumens (6000K CCT, 70CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	4,635	5,683	7,034	7,717
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	136	129	121	117
T2R	Lumens	4,962	6,084	7,531	8,262
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	146	138	130	125
T3	Lumens	4,736	5,808	7,189	7,886
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
T3R	Lumens	4,816	5,907	7,310	8,020
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	142	134	126	122
T4FT	Lumens	4,772	5,852	7,242	7,945
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	140	133	125	120
T4W	Lumens	4,679	5,738	7,103	7,791
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G2
	Lumens per Watt	138	130	122	118
SL2	Lumens	4,643	5,693	7,045	7,728
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B2-U0-G3
	Lumens per Watt	137	129	121	117
SL3	Lumens	4,729	5,800	7,178	7,873
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	139	132	124	119
SL4	Lumens	4,518	5,540	6,856	7,520
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G3	B1-U0-G3
	Lumens per Watt	133	126	118	114
5NQ	Lumens	4,868	5,969	7,387	8,104
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	143	136	127	123
5MQ	Lumens	5,043	6,184	7,654	8,396
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	148	141	132	127
5WQ	Lumens	4,926	6,041	7,476	8,201
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G2	B3-U0-G2
	Lumens per Watt	145	137	129	124
SLL/ SLR	Lumens	4,181	5,129	6,348	6,964
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	123	117	109	106
RW	Lumens	4,839	5,934	7,345	8,058
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	142	135	127	122
AFL	Lumens	4,852	5,948	7,362	8,077
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	143	135	127	122

Nominal Power Lumens (2700K CCT, 80CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	3,408	4,178	5,172	5,673
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	100	95	89	86
T2R	Lumens	3,648	4,473	5,536	6,074
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	107	102	95	92
T3	Lumens	3,482	4,270	5,285	5,797
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G2
	Lumens per Watt	102	97	91	88
T3R	Lumens	3,540	4,342	5,374	5,896
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	104	99	93	89
T4FT	Lumens	3,508	4,302	5,324	5,840
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	103	98	92	88
T4W	Lumens	3,440	4,218	5,222	5,727
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	101	96	90	87
SL2	Lumens	3,413	4,185	5,179	5,681
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	100	95	89	86
SL3	Lumens	3,476	4,264	5,277	5,788
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	102	97	91	88
SL4	Lumens	3,321	4,073	5,040	5,528
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
5NQ	Lumens	3,579	4,387	5,431	5,958
	BUG Rating	B2-U0-G0	B2-U0-G0	B2-U0-G1	B2-U0-G1
	Lumens per Watt	105	100	94	90
5MQ	Lumens	3,707	4,545	5,627	6,172
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	109	103	97	94
5WQ	Lumens	3,621	4,442	5,496	6,029
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	106	101	95	91
SLL/ SLR	Lumens	3,074	3,770	4,667	5,120
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	90	86	80	78
RW	Lumens	3,557	4,363	5,399	5,924
	BUG Rating	B2-U0-G1	B2-U0-G1	B2-U0-G1	B3-U0-G1
	Lumens per Watt	105	99	93	90
AFL	Lumens	3,567	4,373	5,412	5,938
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	105	99	93	90

Nominal Power Lumens (3000K CCT, 80CRI)

Number of Light Squares		SA1A	SA1B	SA1C	SA1D
LED Drive Current		600mA	800mA	1A	1.2A
Optics					
T2	Lumens	3,684	4,517	5,590	6,132
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	108	103	96	93
T2R	Lumens	3,943	4,835	5,984	6,566
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	116	110	103	99
T3	Lumens	3,763	4,615	5,713	6,267
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	111	105	99	95
T3R	Lumens	3,827	4,694	5,809	6,373
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G2	B1-U0-G2
	Lumens per Watt	113	107	100	97
T4FT	Lumens	3,792	4,650	5,756	6,313
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	112	106	99	96
T4W	Lumens	3,718	4,560	5,644	6,191
	BUG Rating	B1-U0-G1	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	109	104	97	94
SL2	Lumens	3,690	4,524	5,598	6,141
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	109	103	97	93
SL3	Lumens	3,758	4,609	5,705	6,256
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	111	105	98	95
SL4	Lumens	3,590	4,402	5,448	5,976
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G3
	Lumens per Watt	106	100	94	91
5NQ	Lumens	3,868	4,742	5,871	6,441
	BUG Rating	B2-U0-G0	B2-U0-G1	B2-U0-G1	B2-U0-G1
	Lumens per Watt	114	108	101	98
5MQ	Lumens	4,007	4,913	6,082	6,672
	BUG Rating	B2-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	118	112	105	101
5WQ	Lumens	3,914	4,801	5,941	6,517
	BUG Rating	B3-U0-G1	B3-U0-G1	B3-U0-G1	B3-U0-G2
	Lumens per Watt	115	109	102	99
SLL/ SLR	Lumens	3,323	4,076	5,044	5,535
	BUG Rating	B1-U0-G2	B1-U0-G2	B1-U0-G2	B1-U0-G2
	Lumens per Watt	98	93	87	84
RW	Lumens	3,844	4,716	5,837	6,403
	BUG Rating	B2-U0-G1	B2-U0-G1	B3-U0-G1	B3-U0-G1
	Lumens per Watt	113	107	101	97
AFL	Lumens	3,856	4,727	5,850	6,418
	BUG Rating	B1-U0-G1	B1-U0-G1	B1-U0-G1	B1-U0-G1
	Lumens per Watt	113	107	101	97

Energy and Performance Data

Nominal Power Lumens (2200K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (2700K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (3000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (5000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (6000K CCT, 70 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (2700K CCT, 80 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25

Nominal Power Lumens (3000K CCT, 80 CRI)

Number of Light Squares	SA1A	SA1B	SA1C	SA1D
Drive Current	600mA	800mA	1A	1.2A
Nominal Power (Watts)	34	44	58	66
Input Current @ 120V (A)	0.30	0.39	0.51	0.58
Input Current @ 277V (A)	0.14	0.17	0.23	0.25